

Job: _____
 Model: _____
 Type: _____
 Date: _____

internal

AC only: 120/277V input. Self-Powered: 120/277V input. The **PACO PX** self powered version uses a rechargeable, maintenance free 3.6V 900mAH nickel cadmium battery. The circuit board features an onboard solid state transformer, low voltage disconnect and brownout protection. Red or green LEDs totaling less than 2W.

external

The **PACO PX** features performance and reliability in a compact, attractive and low profile package. It is constructed from high impact, injection molded thermoplastic. The **PX** comes standard in white, black is optional. Field adjustable chevrons are standard. The **PX** can be universally mounted single or double face (extra faceplate included). The SA version includes an integrated test switch / monitor LED, which gives immediate unit status. Damp location rated.

dimensions (in,mm.)

Series	A	B	C	D	E	F
PX	7.2"	11.6"	12.6"	8.2"	4.3"	2"
	183mm	295mm	320mm	209mm	109mm	51mm



ordering information

Model	Description
PXGHT	Paco exit, AC only, green LED, universal face, white
PXGSA	Paco exit, Ni-Cd battery, green LED, universal face, white
PXGSAAT	Paco exit, Ni-Cd battery, green LED, universal face, autotest, white
PXGSARC	Paco exit, Ni-Cd battery, green LED, universal face, 3.4W remote capable, white
PXRHT	Paco exit, AC only, red LED, universal face, white
PXRSA	Paco exit, Ni-Cd battery, red LED, universal face, white
PXRSAAT	Paco exit, Ni-Cd battery, red LED, universal face, autotest, white
PXRSAATRC	Paco exit, Ni-Cd battery, red LED, universal face, autotest, 3.4W remote capable, white
PXRSAB	Paco exit, Ni-Cd battery, red LED, universal face, black
PXRSARC	Paco exit, Ni-Cd battery, red LED, universal face, 3.4W remote capable, white

Accessories

WG3DX16.5LX14WWHT Wire guard (wall mount), white

■ emergency heads

The **PACO(PX)** has remote capable option (RC) to operate single or double head remotes. Max load per unit: 3.4W. Compatible with Beghelli Paco PS (1.7W/ head), PR (0.6W/ head) and PRWP (1.17W/ head) remote heads only.

■ electrical

BATTERY: The **PX** is designed with a 3.6V 900mAH maintenance free nickel cadmium battery that provides minimum emergency duration of 90 minutes. The recharge time of the battery is 24 hours. The battery operating temperature is from 50°F up to 104°F(10°C up to 40°C).

CIRCUIT: The **PX** has a 120/277V solid state transformer. Low voltage disconnect and brownout protection are standard. Red or green LEDs totaling <2W.

■ mechanical

The **PX** is designed for surface wall or ceiling installations. Suitable for indoor/ damp location environments. The thermoplastic housing comes in white as standard; optional black is available. The **PACO** is a universal exit available with or without battery back-up. The exit comes standard with mounting canopy and extra stencil face plate.

■ self-powered

The **PX** self-powered is designed to operate on battery power in the event of regular / mains power failure. Both the battery and charger are completely contained within the standard sign. There are no external components and no alterations made to the external dimensions of the standard sign. Status is easily determined via an LED that indicates AC-ON. A push button test switch allows maintenance personnel to quickly confirm the operational status of the exit at any time.

■ warranty

The **PX** comes with a 5-year factory warranty. Deliberate damage, misuse, improper installation effectively void the warranty. For complete warranty details see online.